

ALLIANCE

Specification Sheet

Model: it300 (300 Watt Intelligent Transformer)

Description: Low voltage magnetic power supply suitable for indoor or outdoor use



Notes:

Project:
Type:

Specifications:

Max Amperage (Load):	2.5 amps
Max Input (Primary Voltage):	120 volts
Secondary Voltage:	12 volts*
Available Voltage Taps:	14v, 14v, 14v
Exterior Construction:	Stainless Steel
Warranty:	Lifetime
Certification:	UL Listed to U.S. and Canadian safety standards for low voltage landscape lighting.



Features:

- Multiple Taps (14v)
- Bluetooth Ready
- Astronomical Timer
- Phone App Driven
- Pre-loaded Programs



Getting Started:

Step 1: Download it.

Scan the QR code or go to the Play Store if you have an android phone or to the App Store if you have an iphone. Search "Intelligent Transformer" and look for the "it" app icon. Download and install the app.

Step 2: Plug it in.

Plug in your transformer and bring up the app on your phone (be sure the Bluetooth is enabled). The app will find your transformer by its specific serial number. Click on the serial number to start using your transformer. You could rename your transformer to anything you like.

Step 3: Program your setting.

Use your phone to set your desired on and off times, or just let "it" use the default setting of sunset to sunrise.