

# ALLIANCE

## Specification Sheet

### Model: XF600 (600 Watt Transformer)

Description: Low voltage power supply suitable for indoor or outdoor use



Notes:

Project:
Type:

#### Specifications:

<b>Max Amperage (Load):</b>	5 amps
<b>Max Input (Primary Voltage):</b>	120 volts
<b>Secondary Voltage:</b>	12-17 volts*
<b>Available Voltage Taps:</b>	12,13,14,15,16,17,18
<b>Exterior Construction:</b>	Stainless Steel
<b>Warranty:</b>	Lifetime Warranty
<b>Certification:</b>	UL Listed to U.S. and Canadian safety standards for low voltage landscape lighting (UL 2108)



\*You may use any combination of output terminal lugs (12-18 volt). However you may not exceed 600 watts on any single terminal lug.

#### Features:

- Fully potted, insulated, single core transformer
- Inline surge protection
- Easy on/off, secondary breaker switches on each common tap
- Stainless steel cabinet with removable and lockable latched door
- Multiple voltage taps ranging from 12 to 20 volts
- Two common lug terminals
- Tilted lug bar where the secondary lugs will be easier to access and install. The adjusted lug bar eliminates the blind spots that occur when trying to install low voltage wire to the terminal lug.
- Relay installed to bring the amperage delivered to the timer and photocells down to a lower level thus improving the longevity of life to those accessories and eliminating failures.
- Amp loop that provides contractors with one easy point of reference to check the primary amperage on the transformer
- Snap-In photocell ready receptacles
- Removable bottom panel allowing for easy access to lug terminal, more room for wiring, and the ability to attach conduits through the five knockouts.

#### Accessories Available:

Transformer Accessories:
ITIMER - Phone App Driven Astronomical Timer
TIMER - Mechanical Timer
PC - Photocell